


# BI2-G12-AZ31X-B3131


## Inductive Sensor



### Features

- Threaded barrel, M12 x 1
- Chrome-plated brass
- AC 2-wire, 20...250 VDC
- DC 2-wire, 10...300 VDC
- NO contact
- 1/2" male connector

### Wiring diagram



### Technical data

|                                  |   |
|----------------------------------|---|
| Type                             | BI2-G12-AZ31X-B3131                                 |
| ID                               | 13502   |
| <b>General data</b>              |   |
| Rated switching distance         | 2 mm  |
| Mounting conditions              | Flush   |
| Secured operating distance       | $\leq (0.81 \times S_n)$ mm                         |
| Correction factors               | St37 = 1; Al = 0.3; stainless steel = 0.7; Ms = 0.4 |
| Repeat accuracy                  | $\leq 2$ % of full scale                            |
| Temperature drift                | $\leq \pm 10$ %                                     |
| Hysteresis                       | 3...15 %  |
| <b>Electrical data</b>           |   |
| Operating voltage $U_b$          | 20...250 VAC  |
| Operating voltage $U_b$          | 10...300 VDC  |
| AC rated operational current     | $\leq 100$ mA                                       |
| DC rated operating current $I_b$ | $\leq 100$ mA                                       |
| Frequency                        | $\geq 50... \leq 60$ Hz                             |
| Residual current                 | $\leq 1.7$ mA                                       |
| Isolation test voltage           | 1.5 kV  |
| Surge current                    | $\leq 1$ A ( $\leq 10$ ms max. 5 Hz)                |
| Voltage drop at $I_b$            | $\leq 6$ V  |
| Output function                  | 2-wire, NO contact, 2-wire                          |
| Smallest operating current       | $\geq 3$ mA   |
| Switching frequency              | 0.02 kHz  |

### Functional principle

Inductive sensors detect metal objects contactless and wear-free. For this, they use a high-frequency electromagnetic AC field that interacts with the target. Inductive sensors generate this field via an RLC circuit with a ferrite coil.

Technical data

| Mechanical data                       |  |
|---------------------------------------|--|
| Design                                | Threaded barrel, M12 x 1                   |
| Dimensions                            | 71 mm                                      |
| Housing material                      | Metal, CuZn, Chrome-plated                 |
| Active area material                  | Plastic, PA12-GF30                         |
| Max. tightening torque of housing nut | 10 Nm                                      |
| Electrical connection                 | Connector, 1/2"                            |
| Environmental conditions              |  |
| Ambient temperature                   | -25...+70 °C                               |
| Vibration resistance                  | 55 Hz (1 mm)                               |
| Shock resistance                      | 30 g (11 ms)                               |
| Protection class                      | IP67                                       |
| MTTF                                  | 2283 years acc. to SN 29500 (Ed. 99) 40 °C |
| Switching state                       | LED, Red                                   |

Mounting instructions

Mounting instructions/Description

Diagram showing the side view of the mounting bracket. Dimension T is indicated as the distance from the center of the active area to the edge of the bracket.

Diagram showing the top view of the mounting bracket. Dimension G is indicated as the distance between the centers of the two active areas.

Diagram showing the front view of the mounting bracket. Dimensions D, S, and W are indicated. D is the distance from the center of the active area to the edge of the bracket. S is the distance from the center of the active area to the edge of the bracket. W is the distance from the center of the active area to the edge of the bracket.

|                        |         |
|------------------------|---------|
| Distance D             | 2 x B   |
| Distance W             | 3 x Sn  |
| Distance T             | 3 x B   |
| Distance S             | 1.5 x B |
| Distance G             | 6 x Sn  |
| Diameter active area B | Ø 12 mm |

BI2-G12-AZ31X-B3131 | 02/21/2025 14-32 | technical changes reserved

## Accessories

QM-12

6945101

Quick-mount bracket with dead-stop; material: Chrome-plated brass. Male thread M16 × 1. Note: The switching distance of the proximity switches may change when using quick-mount brackets.



BST-12B

6947212

Mounting clamp for threaded barrel sensors, with dead-stop; material: PA6



MW12

6945003

Mounting bracket for threaded barrel sensors; material: Stainless steel A2 1.4301 (AISI 304)



BSS-12

6901321

Mounting clamp for smooth and threaded barrel sensors; material: Polypropylene

