


# NI20-Q14-AP6X2

## Inductive Sensor



### Features

- Rectangular, height 14 mm
- Active face on top
- Plastic, PBT-GF30-V0
- DC 3-wire, 10...30 VDC
- NO contact, PNP output
- Cable connection

### Wiring diagram



### Technical data

|                                        |                                                     |
|----------------------------------------|-----------------------------------------------------|
| Type                                   | NI20-Q14-AP6X2                                      |
| ID                                     | 4690205                                             |
| <b>General data</b>                    |                                                     |
| Rated switching distance               | 20 mm                                               |
| Mounting conditions                    | Non-flush                                           |
| Secured operating distance             | $\leq (0.81 \times S_n)$ mm                         |
| Correction factors                     | St37 = 1; Al = 0.3; stainless steel = 0.7; Ms = 0.4 |
| Repeat accuracy                        | $\leq 2$ % of full scale                            |
| Temperature drift                      | $\leq \pm 10$ %                                     |
| Hysteresis                             | 3...15 %                                            |
| <b>Electrical data</b>                 |                                                     |
| Operating voltage $U_B$                | 10...30 VDC                                         |
| Ripple $U_{ss}$                        | $\leq 10$ % $U_{Bmax}$                              |
| DC rated operating current $I_B$       | $\leq 200$ mA                                       |
| No-load current                        | $\leq 15$ mA                                        |
| Residual current                       | $\leq 0.1$ mA                                       |
| Isolation test voltage                 | 0.5 kV                                              |
| Short-circuit protection               | yes/Cyclic                                          |
| Voltage drop at $I_B$                  | $\leq 1.8$ V                                        |
| Wire break/reverse polarity protection | yes/Complete                                        |
| Output function                        | 3-wire, NO contact, PNP                             |
| Switching frequency                    | 0.25 kHz                                            |

### Functional principle

Inductive sensors detect metal objects contactless and wear-free. For this, they use a high-frequency electromagnetic AC field that interacts with the target. Inductive sensors generate this field via an RLC circuit with a ferrite coil.



## Accessories

MW-Q14/Q20

6945006

Mounting bracket for rectangular Q14  
or Q20; material VA 1.4301

