

Industri<mark>al</mark> Automation

How to Setup and Connect

👸 to IM Modules in Pactware



G1009 Revised 1/15/2014

ABOUT THIS GUIDE

This "How to" is intended to show the user how to setup and connect to IM modules in Pactware.

REQUIRED PARTS

Hardware

• IM-PROG III cable

Software

- Windows 7
- Pactware 4.1
- IM-PROG III Driver

CONFIGURE PACTWARE

Important Note: The serial to IM module cable part number is the IM-PROG III and MUST be used to insure proper communication to the device.

Open up Pactware



Right click HOST PC and Add device



Select HART Communication and click OK

2.4	10日日本					
20000						
	A Decise Res					
	dar-tar	< Print .	Sandar .	in the second se	Denies Neutron	
	8.5ma15(1)	R. Santa	fact.	(17W specific	1.047 (811 81-1)	
	THE CONTRACTORY	(del)	(Gaven)	(##+)%F	3.0.00 (00.0040 00)	
	- Not Generalized	91120M				
	. Mar Canada and	97 L 2 674				
	• Mill Generation A	01130m			3 (aux)	
	• With Connected on P	57120W		ure	a cear	
	• • • • • • • • • • • • • • • • • • •	en i zener supp T U DP	orted by CK	ure	9 000	
	· Stat Conversion A	91110 Supp TUR	orted by CK	ure	9 000	
	a ^{NET} Constants	91110M Supp TUR	orted by CK	me	9. Oner	
	. Mit Consecution	91110M Supp TUR	orted by CK	anc	a our	
	. Nor Conversion A	9120M Supp TUR	orted by CK	ane	9. Omr.	
	. With Conservation of	supp TUR	ortied by CK	m	9 (met	
	. Mar Concelution	ST LLUM Supp TUR	orted by CK	an	9 <u>9</u>	
		STILLER Supp TUR	orted by CK	me	9 999	
	. State Later 1	91110M Supp TUR	orted by CK	me	9 900	

Double click COM1 and Setup the following Parameters. Then click Apply, and click Ok

Philippe		101
The ER Have Posts Davis Ditter Miller Mil		
1	1 1	
Anat B.A. CONTRACTO		111
Interior Address (
1 41 K		
Conversion and an	Patt rubben I	1
trad-aces	13bi Camaiodan Fat	
	Tantas Indiana	
	ATS Care I	
1967 policy	Nate Proprieto A	
and the second se	Preside P B	
	Handae of construction a	
	when all	
Address and	Butather P	
	fod attes 2	
		OK Canal Apply
8 X		
do enclareto Abrahar		
28ar 6009300000 254m	ne (14	e Hittenet Kin. e giel

Scroll the mouse over the Device Catalog icon and select the correct IM device



(If the IM device is not listed, you must go to the German website (www.turck.de/en/) and search by part number for the device. Once you find the device, download the "configuration software".

Exit PACTWARE and install the "configuration software" of the device. After the "configuration software" is finished installing, reopen PACTWARE. You should see the correct device listed in the device catalog.

If the IM device is listed, go to next step.)

Highlight and "ADD" the device. Hit F3 to clear the Device catalog screen. Next, right click COM1 and click CONNECT.



Highlight and right click "-/-" and click CONNECT



Next, right click "-/-", go to "Parameter" and "Online parameterization"



You should now be able to setup all the parameters of the device. If you require additional support; please contact TURCK and ask for Applications Support.

