


NI30-K40SR-VP4X2 Inductive Sensor

Features


- 2 cable entries (axial, radial)
- Smooth barrel, Ø 40 mm
- Plastic, ABS
- DC 4-wire, 10...65 VDC
- Changeover contact, PNP output
- Terminal chamber

Wiring diagram



Functional principle

Inductive sensors detect metal objects contactless and wear-free. For this, they use a high-frequency electromagnetic AC field that interacts with the target. Inductive sensors generate this field via an RLC circuit with a ferrite coil.



Technical data

Type	NI30-K40SR-VP4X2
ID	15658
General data	
Rated switching distance	30 mm
Mounting conditions	Non-flush
Secured operating distance	$\leq (0.81 \times S_n)$ mm
Correction factors	St37 = 1; Al = 0.3; stainless steel = 0.7; Ms = 0.4
Repeat accuracy	≤ 2 % of full scale
Temperature drift	$\leq \pm 10$ %
Hysteresis	3...15 %
Electrical data	
Operating voltage U_B	10...65 VDC
Ripple U_{ss}	≤ 10 % U_{Bmax}
DC rated operating current I_o	≤ 200 mA
No-load current	≤ 15 mA
Residual current	≤ 0.1 mA
Isolation test voltage	0.5 kV
Short-circuit protection	yes/Cyclic
Voltage drop at I_o	≤ 1.8 V
Wire break/reverse polarity protection	yes/Complete
Output function	4-wire, Complementary contact, PNP
Switching frequency	0.1 kHz

Technical data

Mechanical data	
Design	Smooth barrel, 40 mm
Dimensions	90 mm
Housing material	Plastic, ABS, Yellow
Active area material	Plastic, ABS, yellow
Electrical connection	Terminal chamber
Clamping ability	≤ 2.5 mm²
Environmental conditions	
Ambient temperature	-25...+70 °C
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 g (11 ms)
Protection class	IP67
MTTF	2283 years acc. to SN 29500 (Ed. 99) 40 °C
Power-on indication	LED, Green
Switching state	LED, Yellow
Included in delivery	BS 40, cable gland, dummy plug

Mounting instructions

Mounting instructions/Description

The image contains three technical diagrams illustrating the mounting of the BS 40 sensor. The top diagram shows a side view of the sensor (a grey rectangular block with two yellow cylindrical active areas) being mounted onto a grey rectangular panel. Dimensions are indicated: 'N' is the distance between the two active areas, 'S' is the distance from the panel edge to the first active area, 'D' is the distance between the two active areas, and 'W' is the total width of the panel. The bottom left diagram shows a top view of the sensor mounted on a panel, with 'T' indicating the thickness of the panel. The bottom right diagram shows a side view of the sensor mounted on a cable gland, with 'G' indicating the distance from the gland edge to the active area.

Distance D	3 x B
Distance W	3 x Sn
Distance T	3 x B
Distance S	1.5 x B
Distance G	6 x Sn
Distance N	40 mm
Diameter active area B	Ø 40 mm

NI30-K40SR-VP4X2 | 02/21/2025 13-11 | technical changes reserved

Accessories

BS 40

69466

Fixing clamp; material mounting
block: PBT

