


# NI10-G18-AN7X 60MM


## Inductive Sensor



### Features

- Threaded barrel, M18 x 1
- Chrome-plated brass
- DC 3-wire, 10...30 VDC
- NO contact, NPN output
- TTL compatible
- Cable connection

### Wiring diagram



### Technical data

|                                        |                                                     |
|----------------------------------------|-----------------------------------------------------|
| Type                                   | NI10-G18-AN7X 60MM                                  |
| ID                                     | 4740799                                             |
| General data                           |                                                     |
| Rated switching distance               | 10 mm                                               |
| Mounting conditions                    | Non-flush                                           |
| Secured operating distance             | $\leq (0.81 \times S_n)$ mm                         |
| Correction factors                     | St37 = 1; Al = 0.3; stainless steel = 0.7; Ms = 0.4 |
| Repeat accuracy                        | $\leq 2$ % of full scale                            |
| Hysteresis                             | 3...15 %                                            |
| Electrical data                        |                                                     |
| Operating voltage $U_B$                | 10...30 VDC                                         |
| Ripple $U_{ss}$                        | $\leq 10$ % $U_{Bmax}$                              |
| DC rated operating current $I_o$       | $\leq 200$ mA                                       |
| No-load current                        | $\leq 10$ mA                                        |
| Residual current                       | $\leq 0.1$ mA                                       |
| Isolation test voltage                 | 0.5 kV                                              |
| Short-circuit protection               | no                                                  |
| Voltage drop at $I_o$                  | $\leq 0.7$ V                                        |
| Wire break/reverse polarity protection | yes/yes (voltage supply)                            |
| Output function                        | 3-wire, NO contact, NPN                             |
| Switching frequency                    | 0.5 kHz                                             |
| Mechanical data                        |                                                     |
| Design                                 | Threaded barrel, M18 x 1                            |

### Functional principle

Inductive sensors detect metal objects contactless and wear-free. For this, they use a high-frequency electromagnetic AC field that interacts with the target. Inductive sensors generate this field via an RLC circuit with a ferrite coil.

## Technical data

|                                       |                                            |
|---------------------------------------|--------------------------------------------|
| Dimensions                            | 64 mm                                      |
| Housing material                      | Metal, CuZn, Chrome-plated                 |
| Active area material                  | Plastic, PA12-GF30                         |
| End cap                               | Plastic, EPTR                              |
| Max. tightening torque of housing nut | 25 Nm                                      |
| Electrical connection                 | Cable                                      |
| Cable quality                         | Ø 5.2 mm, LifYY, PVC, 2 m                  |
| Core cross-section                    | 3 x 0.34 mm <sup>2</sup>                   |
| <b>Environmental conditions</b>       |                                            |
| Ambient temperature                   | -25...+70 °C                               |
| Vibration resistance                  | 55 Hz (1 mm)                               |
| Shock resistance                      | 30 g (11 ms)                               |
| Protection class                      | IP67                                       |
| MTTF                                  | 2283 years acc. to SN 29500 (Ed. 99) 40 °C |
| Switching state                       | LED, Yellow                                |


## Mounting instructions

| Mounting instructions/Description |            |
|-----------------------------------|------------|
|                                   | Distance D |
|                                   | 3 x B      |
|                                   | Distance W |
|                                   | 3 x Sn     |
|                                   | Distance T |
|                                   | 3 x B      |
|                                   | Distance S |
|                                   | 1.5 x B    |
|                                   | Distance G |
|                                   | 6 x Sn     |
|                                   | Distance N |
|                                   | 2 x Sn     |
| Diameter active area B            |            |
| Ø 18 mm                           |            |

## Accessories

MW18


6945004



Mounting bracket for threaded barrel sensors; material: Stainless steel A2 1.4301 (AISI 304)

BSS-18


6901320



Mounting clamp for smooth and threaded barrel sensors; material: Polypropylene

QM-18

6945102



Quick-mount bracket with dead-stop; material: Chrome-plated brass. Male thread M24 × 1.5. Note: The switching distance of the proximity switches may change when using quick-mount brackets.